

Analog valve Positioner, Valve Positioners, 4-20mA, 0-20mA, 0-10V input, intrinsically safe, ATEX , FM, CSA

SRI986

# Main

Range of Product	Valve Positioners
Product or Component Type	Valve positioner
Communication port protocol	HART, 420 mA
Market Segment	Process industry

# Complementary

Input type	Current 420 mA Current 020 mA Voltage 010 V	
Housing material	Aluminium alloy	
Input pressure	1.46 bar 2090 psi	
Stroke range	8200 mm	
Maximum hysteresis	0.3 %	
Linearity	< 1 % of the travel span	
Pneumatic operation	Single acting Double acting	
Operating angle	30180 °	

### **Environment**

Ambient Air Temperature for Operation	-40176 °F (-4080 °C) -4080 °C (-40176 °F)	
IP Degree of Protection	IP54	
Product certifications	ATEX FM CSA	

# **Packing Units**

Unit Type of Package 1	PCE	
Nbr. of units in pkg.	1	

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

#### Environmental Data explained >

How we assess product sustainability >

∇ Environmental footprint	
Carbon footprint (kg CO2 eq, Total Life cycle)	79
Environmental Disclosure	Product Environmental Profile

#### **Use Better**

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant with Exemptions
REACh Regulation	REACh Declaration
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

## Use Again

○ Repack and remanufacture	
Circularity Profile	End of Life Information
Take-back	No
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.